

General Purpose Motors [Model No. U140256C]

1, Technical Info:

Frame: 56C

Horsepower: 2 HP

Amperage: 20.0/10.0

Frequency: 60 HZ

Shaft Length: 1.88"

Motor Reversible

Phase: One/ Single Phase

Voltage: 115V/230V


RPM: 1750 RPM

Shaft Diameter: 5/8" Keyed shaft

Rotation: CW/CCW

Overload Protection with Manual Reset

2, Connection Method:



- At 115V, No.5 connect a power cable, No. 1,3 & 8, three lines together to connect another power cable. INS means keep insulated, the remaining 5 lines, all together, are isolated with non-conducting objects.
- At 230V, the same operation as 115V.
- Changed from CCW to CW is the exchange of 6 and 8.